

AUTOMATE™

DCRF 3.0

Simplified wiring. Efficient installation. Maintenance free.
This low voltage motor is perfect for small to large Roller shade applications.



BIDIRECTIONAL COMMUNICATION

Automate Radio Communication utilizes two-way communication to provide up-to-date feedback on battery levels and shade positioning via the Automate Pulse 2 app.



ADJUSTABLE SPEED CONTROL

Three shade speed settings to suit your needs – faster for larger shades, slower for smaller. Features quiet operation when set to the lowest speed setting.



SIMPLIFIED SETUP

Whether using a remote control or app for shade setup, Automate programming instructions are streamlined to have your shades moving as quickly as possible.




FAVORITE POSITIONING

Add a programmable shade position in addition to the upper and lower limits that can be defined as your "favorite".



PRECISE LIMIT ADJUSTMENT

Incremental steps during limit setting allows for precise positioning of the shade.



Automate Radio
Communication


7 YEAR
WARRANTY

PRODUCT SPECIFICATIONS

Part #: MTDCRF35-3 Automate DCRF 3.0


Voltage	12V DC	Limit Switch Type	Electronic
Torque	3.0Nm	Current	2.2A
Max Run Time	12 Min	Battery Size/Type	External Battery Pack
Speed	28 RPM (Adjustable to 24 or 20)	Temp Working Range	32°F to 140°F (0°C to 60°C)
Radio Frequency	433.92 MHz	Insulation Class	III
RF Modulation	FSK	Sound Level	~53 dB
IP Rating	IP44	Power	26W

DIMENSIONS




COMPATIBLE PARTS

Tubes



Crown & Drives



Adaptors



S45 - Light	MTCRDR-35-S45
S45 - Std	
S45 - HD	
2" Ribbed Tube	MTCRDR-35-2


- MTAD-252835-SL
- MTAD-25-28-SLV2W
- MTAD-252835-RS
- RB40-1402-069400

COMPATIBLE SYSTEMS

- S45 Roller Shades
- Skyline Roller Shades
- R Series Roller Shades

COMPATIBLE PRODUCTS (refer to catalog for full item listings)

Controllers



Charging Options

